

Reg No.: \_\_\_\_\_

Name: \_\_\_\_\_

**APJ ABDUL KALAM TECHNOLOGICAL UNIVERSITY**

Seventh Semester B.Tech Degree Examination (Regular and Supplementary), December 2020

**Course Code: EC401****Course Name: INFORMATION THEORY & CODING**

Max. Marks: 100

Duration: 3 Hours

**PART A***Answer any two full questions, each carries 15 marks.*

Marks

- 1 a) Find the self information of two messages with respective probabilities 0.1 and 0.9. Comment on the results. (3)
- b) Prove that mutual information of a channel is symmetric and always non-negative. (5)
- c) Joint probability matrix of a discrete channel is given below: (7)
- $$P(X,Y) = \begin{bmatrix} 0.3 & 0.2 & 0.1 \\ 0.1 & 0.1 & 0.2 \end{bmatrix}$$
- Determine the different entropies and verify their relationships.
- 2 a) State and prove noiseless coding theorem. (5)
- b) An analog signal is band limited to 3.4 kHz and is sampled at Nyquist rate. The samples are quantized into 4 levels. The quantization levels are assumed to be independent and occur with probabilities  $p_1 = \frac{1}{2}; p_2 = \frac{1}{4}; p_3 = p_4 = \frac{1}{8}$ . Find the information rate of the source. (4)
- c) Find binary Huffman code for random variable  $S = \{s_1, s_2, s_3, s_4, s_5, s_6, s_7, s_8\}$  with probabilities (0.4, 0.25, 0.15, 0.06, 0.05, 0.04, 0.03, 0.02). Move the combined symbol as high as possible. Find average code word length and efficiency. (6)
- 3 a) Consider a message ensemble  $S = \{s_1, s_2, s_3, s_4, s_5, s_6\}$  with probabilities  $P = \{1/3, 1/4, 1/8, 1/8, 1/12, 1/12\}$ . Construct a binary code and determine its efficiency using Shannon – Fano coding procedure. (5)
- b) Explain binary symmetric and binary erasure channels. Derive the expression for their channel capacities. (10)

**PART B***Answer any two full questions, each carries 15 marks.*

- 4 a) What are the properties to be satisfied by a linear block code? Illustrate with an example. (5)
- b) What is the capacity of a channel of infinite bandwidth? (5)
- c) Define the terms Hamming weight, Hamming distance and minimum Hamming distance with suitable example. (5)
- 5 a) Explain band width – SNR trade off in a Gaussian channel. (5)

- b) For a systematic (7,4) linear block code, the parity matrix  $P$  is given by (10)

$$P = \begin{bmatrix} 1 & 1 & 1 \\ 1 & 1 & 0 \\ 1 & 0 & 1 \\ 0 & 1 & 1 \end{bmatrix}$$

(i) Find all possible valid code vectors. (ii) Draw the encoder circuit. (iii) Draw the syndrome calculation circuit.

- 6 a) If  $V$  is a valid code vector, prove that  $VH^T = 0$ , where  $H$  is parity check matrix. (5)  
 b) State and prove Shannon – Hartley theorem. (10)

### PART C

*Answer any two full questions, each carries 20 marks.*

- 7 a) Draw a (2,1,3) encoder with impulse sequences  $g^{(1)} = 1011$  and  $g^{(2)} = 1111$ . (12)  
 Find the generator matrix for the given encoder. Also find the code vector for the message 11010 by time and frequency domain approaches.  
 b) What is a BCH code? Find the generator polynomial for single, double and triple error correcting BCH code of block length,  $n = 15$ . (8)
- 8 a) What are the properties to be satisfied by a cyclic code? (5)  
 b) For a non-systematic rate  $\frac{1}{2}$  code given by  $g^{(1)} = 111$  and  $g^{(2)} = 101$ . Draw the graph, trellis and state diagram. (10)  
 c) What are the features of Reed-Solomon codes? (5)
- 9 a) Explain how systematic encoding is achieved in cyclic codes. For a systematic (7, 4) cyclic code, find the code vector corresponding to message  $u(x) = 1 + x^3$ , generated by  $g(x) = 1 + x + x^3$ . (10)  
 b) For a convolutional encoder with generator sequences  $g^{(1)} = 100$  and  $g^{(2)} = 101$ , if the received code word is 00100000010000, find the transmitted code word using Viterbi algorithm. (10)

\*\*\*\*